


CURRENT PRODUCTS model:AF320A

3Ø SLAVE CLOCK



SEIKO station clock compatible
Simple time setting
Large digital display
High intensity display
Easy installation
19 inches 2U size

AF320A is the digital display slave clock which is interchangeable with the three-phase slave clock of the station clock. It only mounts XLR plug to an existing cable, and setting can coexist in an existing system without making special modification.

"Time setting"

It switches toggle switch of the rear panel to the SET side and sets Hour, Minute and Second by independence in a rotary switch and it switches it off to the START side and begins a count from the following input pulse when it changes.

"Display"

The display is formalities for 24 hours. A standard LED color is umber, but can change in red, green or yellow. (the picture is yellow, but standard color is umber.)

"Input signal"

It is based on the working in the three-phase 24V pulse, but can count even the single phase clock of the TTL level. In this case, please be connected to 1-2, 1-3, 2-3 either XLR connector, and the polarity does not matter.

"Others"

AF320A counts a three-phase pulse directly. Please note in the possibility that false operation occurs in the very noisy environment. Therefore, please use shield cable for connection as much as possible.





S P E C I F I C A T I O N S

- INPUT: 24V 3 phase clock (opto coupler isolated)
- INPUT CONNECTOR: XLR3-M
- DISPLAY: 57mm LED
- DISPLAY FORMAT: 24 hours
- MAINS: 100VAC 50/60Hz MAX5W
- DIMENSIONS: 482Wx88Hx153D, 4kg

| | | |
|-------------|--------|----------|
| Slave clock | AF320A | ¥320,000 |
|-------------|--------|----------|

accessory : AC cable

The specifications are subject to change without notice.
2-26-11 AKATSUTSUMI, SETAGAYA-KU, TOKYO, 156-0044 JAPAN



| | | |
|--------------------------------|-------------------------------------|-----------------------|
| (c)CURRENT,INC. H.ICHIHASHI | SYNC CLOCK AF320AR PANEL DIAGRAM | Jun.2005 AF320AR-D |
|--------------------------------|-------------------------------------|-----------------------|

SYNC CLOCK AF320/A

概要

S E I K O 社製放送局用システム時計の 3 相小時計と置き換え可能なデジタル表示の同期時計です。各表示桁ごとのつまみとセットスイッチで非常に簡単に時刻設定を行うことが出来ます。


入力

3 相クロック入力は X L R 3 ピンのオスです。接続において各位相は特に考慮する必要はありませんが、1 は赤、2 は青、3 は白を接続して下さい。単相クロックの場合には 1 と 2、1 と 3 または 2 と 3 のいずれかのペアに接続してください。(極性は問いません)

電源

電源は A C 1 0 0 V、5 0 / 6 0 H z を接続して下さい。また、ヒューズは 5 × 2 0 mm タイプの 5 0 m A を使用して下さい。

フロントパネル



リヤパネル

