


CURRENT PRODUCTS model:CSP934

4ch PRO/CONSUMER



Professional to consumer level converter
 Ideal for conversion from +4 to -10
 Jensen made transformer use
 Compact

CSP934 is +4 level of the professional equipment using the Jensen made transformer and 4ch conversion transformer box of the -10 of the consumer equipment. It can cut the ham noise caused by the GND loop and the high frequency noise, too and is extremely useful for sound quality. The small box shape allows the use at every place of a studio or the broadcast scene.

"Converter"

About 14dB is to step down and converts professional equipment and a level of the consumer equipment with a transformer of 4:1. When it uses it to the opposite direction, step-up of about 10dB is possible, but not only step-up is not when it does not drive in sending out impedance less than 50Ω, but also the frequency characteristic turns worse extremely.

"Caution of operation"

It is the passive equipment using the transformer, and, please note for the external inductive noises such as power supply transformers.

"Others"


Please refer about the manufacturing of various equipment using the Jensen transformer.



SPECIFICATIONS

- 🍏 PRO INPUTS: XLR3-F
- 🍏 PRO OUTPUTS: XLR3-M
- 🍏 PRO IMPEDANCE: 34kΩ at 50Ω source with 47kΩ Load
- 🍏 CONSUMER OUTPUTS: RCA
- 🍏 CONSUMER IMPEDANCE: 225Ω at 50Ω source with 47kΩ Load
- 🍏 REFERENCE LEVEL: +4dBu, max=+24dBu
- 🍏 FREQ.RESPONSE: 20 to 20kHz ±0.5dB
- 🍏 THD: <0.01% at Ref.Level
- 🍏 DIMENSIONS: 150Wx50Hx100D 1kg

Pro/Consumer (4ch)	CSP934	¥96,000
accessory : None		



(c)CURRENT,INC.	CSP934 PRO to CONSUMER	Oct.2007
H.ICHIHASHI	PANEL DIAGRAM	CSP934-D